













Pagina - Page																	
TV DI MISURA Measuring VT																	
Codice - Code		TTV003	TTV006	TTV007	TTV010	TTV020	TTV050	TTV100	TTV126	TTV157							
PRESTAZIONI VA - BURDENS VA																	
V	Cl.	1		0,5		1		0,5		1		0,5		1		0,5	
		1	1	0,5	1	0,5	1	0,5	1	0,5	1	0,5	1	0,5	1	0,5	1
100/100 V		3	6	7	14	10	20	20	40	50	100	100	200				
110/100 V		3	6	7	14	10	20	20	40	50	100	100	200				
115/100 V		3	6	7	14	10	20	20	40	50	100	100	200				
220/100 V		3	6	7	14	10	20	20	40	50	100	100	200				
230/100 V		3	6	7	14	10	20	20	40	50	100	100	200				
380/100 V		3	6	7	14	10	20	20	40	50	100	100	200				
400/100 V		3	6	7	14	10	20	20	40	50	100	100	200				
440/100 V		3	6	7	14	10	20	20	40	50	100	100	200				
500/100 V		3	6	7	14	10	20	20	40	50	100	100	200				
600/100 V				7	14	10	20	20	40	50	100	100	200				
720/100 V														50	100	100	200
750/100 V														50	100	100	200
800/100 V						10	20	20	40	50	100	100	200	50	100	100	200
850/100 V														50	100	100	200
900/100 V														50	100	100	200
950/100 V														50	100	100	200
1000/100 V						10	20	20	40	50	100	100	200	50	100	100	200
1050/100 V														50	100	100	200
1100/100 V														50	100	100	200
1150/100 V														50	100	100	200
1200/100 V														50	100	100	200
100:√3/100:√3 V		1,5	3	3,5	7	5	10	8	16	25	50	50	100				
110:√3/100:√3 V		1,5	3	3,5	7	5	10	8	16	25	50	50	100				
115:√3/100:√3 V		1,5	3	3,5	7	5	10	8	16	25	50	50	100				
220:√3/100:√3 V		1,5	3	3,5	7	5	10	8	16	25	50	50	100				
230:√3/100:√3 V		1,5	3	3,5	7	5	10	8	16	25	50	50	100				
380:√3/100:√3 V		1,5	3	3,5	7	5	10	8	16	25	50	50	100				
400:√3/100:√3 V		1,5	3	3,5	7	5	10	8	16	25	50	50	100				
440:√3/100:√3 V		1,5	3	3,5	7	5	10	8	16	25	50	50	100				
500:√3/100:√3 V		1,5	3	3,5	7	5	10	8	16	25	50	50	100				
600:√3/100:√3 V				3,5	7	5	10	8	16	25	50	50	100				
720:√3/100:√3 V														25	50	50	100
750:√3/100:√3 V														25	50	50	100
800:√3/100:√3 V								8	16	25	50	50	100	25	50	50	100
850:√3/100:√3 V														25	50	50	100
900:√3/100:√3 V														25	50	50	100
950:√3/100:√3 V														25	50	50	100
1000:√3/100:√3 V								8	16	25	50	50	100	25	50	50	100
1050:√3/100:√3 V														25	50	50	100
1100:√3/100:√3 V														25	50	50	100
1150:√3/100:√3 V														25	50	50	100
1200:√3/100:√3 V														25	50	50	100



Pagina - Page						
TV DI PRECISIONE High accuracy VT						
Codice - Code		TTV007	TTV010	TTV020	TTV050	TTV100
<b>PRESTAZIONI VA - BURDENS VA</b>						
V	Cl.	0,2	0,2	0,2	0,2	0,2
100/100 V		3	4	8	25	40
110/100 V		3	4	8	25	40
115/100 V		3	4	8	25	40
220/100 V		3	4	8	25	40
230/100 V		3	4	8	25	40
380/100 V		3	4	8	25	40
400/100 V		3	4	8	25	40
440 /100 V		3	4	8	25	40
500/100 V		3	4	8	25	40
600/100 V		3	4	8	25	40
800/100 V				8	25	40
1000 /100 V				8	25	40
100:√3/100:√3 V		1.5	2	4	10	20
110:√3/100:√3 V		1.5	2	4	10	20
115:√3/100:√3 V		1.5	2	4	10	20
220:√3/100:√3 V		1.5	2	4	10	20
230:√3/100:√3 V		1.5	2	4	10	20
380:√3/100:√3 V		1.5	2	4	10	20
400:√3/100:√3 V		1.5	2	4	10	20
440:√3/100:√3 V		1.5	2	4	10	20
500:√3/100:√3 V		1.5	2	4	10	20
600:√3/100:√3 V		1.5	2	4	10	20
800:√3/100:√3 V				4	10	20
1000:√3/100:√3 V				4	10	20



Pagina - Page													
TV DI PRECISIONE High accuracy VT													
Codice - Code		TTV007	TTV010	TTV020	TTV050	TTV100							
<b>PRESTAZIONI VA - BURDENS VA</b>													
V	Cl.	3P		6P		3P		6P		3P		6P	
		3P	6P	3P	6P	3P	6P	3P	6P	3P	6P	3P	6P
100/100 V		20	25	25	35	50	75	100	150	200	300		
110/100 V		20	25	25	35	50	75	100	150	200	300		
115/100 V		20	25	25	35	50	75	100	150	200	300		
220/100 V		20	25	25	35	50	75	100	150	200	300		
230/100 V		20	25	25	35	50	75	100	150	200	300		
380/100 V		20	25	25	35	50	75	100	150	200	300		
400/100 V		20	25	25	35	50	75	100	150	200	300		
440/100 V		20	25	25	35	50	75	100	150	200	300		
500/100 V		20	25	25	35	50	75	100	150	200	300		
600/100 V		20	25	25	35	50	75	100	150	200	300		
800/100 V						50	75	100	150	200	300		
1000/100 V						50	75	100	150	200	300		
100:√3/100:√3 V		10	12	12	15	20	30	50	75	100	150		
110:√3/100:√3 V		10	12	12	15	20	30	50	75	100	150		
115:√3/100:√3 V		10	12	12	15	20	30	50	75	100	150		
220:√3/100:√3 V		10	12	12	15	20	30	50	75	100	150		
230:√3/100:√3 V		10	12	12	15	20	30	50	75	100	150		
380:√3/100:√3 V		10	12	12	15	20	30	50	75	100	150		
400:√3/100:√3 V		10	12	12	15	20	30	50	75	100	150		
440:√3/100:√3 V		10	12	12	15	20	30	50	75	100	150		
500:√3/100:√3 V		10	12	12	15	20	30	50	75	100	150		
600:√3/100:√3 V		10	12	12	15	20	30	50	75	100	150		
800:√3/100:√3 V						20	30	50	75	100	150		
1000:√3/100:√3 V						20	30	50	75	100	150		